



Backup 4 Switch PS 4000

Technical Data Sheet

Product:	Backup 4 Switch PS 4000 manual Backup Switch, DMX only.
Configuration:	High quality anodized aluminium desk housing. Big switcher for manual switching of 2 x 4 DMX 5-pin XLR inputs to 4 x DMX 5-pin XLR outputs. Ideally for switching between main and backup console. Live switching of DMX signals without any lagging. Passive device, no electrical power is needed. RDM compatibility.
Connectivity:	Road Hog 4, Nano Hog 4 Main- and Backup Console (or similar DMX consoles and devices) for switching up to four DMX Universes.
Functions:	Switching between Main and Backup Systems, DMX only.
Circuit Points:	2 x 4 x DMX 5-pin XLR input on the side 1 x 4 x DMX 5-pin XLR output on the back
Compliances:	CE, CETL, ETL
Dimensions and weight:	23.5 x 5.5 x 23.5 cm (w x h x d), 2.0 kg (unpacked)
Order numbers:	15.5905 Backup 4 Switch PS 4000 80.1102 DMX 5-pin patch cable, 0.3m

The delivery is carried out without patch cables.
24 months world wide warranty.

All rights reserved. Errors, literal mistakes and technical changes reserved.
Named brands are the property of their respective company.

© 2012 Arcus Licht- und Präsentationstechnik GmbH



Arcus Licht- und Präsentationstechnik GmbH
Obermeiers Feld 2 - 4, D-33104 Paderborn, Germany
Phone: +49 (0) 5254 93069 0 · Fax: +49 (0) 5254 93069 29

Mail: info@arcus-lighting.com
Web: <http://www.arcus-lighting.com>
Web: <http://www.hog4.de>