



Hedge Hog 4 Console

Technical Data Sheet

Product:	Hedge Hog 4 lighting console for automated luminaires, dimmer and multimedia controllers.
Manufacturer:	High End Systems, Inc., Austin, Texas 78758 USA.
Configuration:	One internal 12.1-inch touchscreen. Robust Hog 4 Operating Software running on an especially adapted Linux system. Internal Hard disk drive (HDD). Real time clock. Ten LED fitted playback controller (Fader, Choose, Go, Pause, Back & Flash), optional expandable. Programming section including four parameter wheel, 12 User Keys, number pad and keys for parameters, groups, timing and effects. One dimmable LED-Desklight.
Connectivity:	Hog 4 and Hog 3 USB Playback Wings are supported. Hog 4 and Hog 3 USB Expansion Wings are supported. MIDI Input and Output, MIDI Show Control and MIDI Timecode via optional external interface. Two onboard DMX XLR 5-pin outputs for fixtures, dimmers and additional DMX capable devices. Ethernet Connector for Art-Net or E1.3.1 (sACN) capable devices. Two USB Ports for Single-, Super DMX Widgets.
Features:	On board processing and distributing of the first two DMX Universes via Art-Net, E1.3.1 (sACN) and two DMX 5-pin XLR outputs on the console, plus up to four DMX XLR 5-pin outputs, realized via optional USB DMX Widgets connected to the console. Almost unlimited amount of Crossfades, Cues, Cue-Lists, Scenes, Chases, Effects, Groups, Palettes, Pages and Macros via dynamic memory management. Booting the console, loading a show or upgrading the software (without reboot) is radical faster than before. Software- and Library-Update via Internet.
Functions:	Graphical Hog 4 User Interface including an extensive fixture library set of all leading manufacturers of DMX, Art-Net or E1.3.1 (sACN) capable devices, derived from Hog 3 User Interface. Grouped configuring and programming, divided into Intensity, Position, Color, Beam. A rich set of Grouping- and Fanning functions. Calibrated Colour Matching System with Color Picker and Gel Charts. Separate Fade, Delay and Effect Times for each individual fixture, parameter and value. Effects Engine with individual control of each Effect Parameter, e.g. Timing, Size, Offset and many more. Can be modified and extended with Effect Templates. Rapid and easy setup of Art-Net outputs, to connect additional devices like multimedia controllers. Fixed Kinds and User Kinds for linked parameters. Pin Code Lock function with a 4-digit PIN to prevent unauthorized access. Saving a show on USB Stick or Hard disk drive is supported.

More data on the next page.



Arcus Licht- und Präsentationstechnik GmbH
 Obermeiers Feld 2 - 4, D-33104 Paderborn, Germany
 Phone: +49 (0) 5254 93069 0 · Fax: +49 (0) 5254 93069 29

Mail: info@arcus-lighting.com
 Web: <http://www.arcus-lighting.com>
 Web: <http://www.hog4.de>



Hedge Hog 4 Console

Technical Data Sheet

Circuit Points:	2 × DMX 5-pin XLR isolated outputs on the back 1 × LAN 1000BaseTX GigaBit Neutrik Ethercon for Fixture-Net on the back 2 × USB on the back 1 × LED desk lights on the top 1 × IEC power port on the back
Electrical requirements:	Mains in 90 - 250VAC, 50/60Hz, 2A maximum
Compliances:	CE, CETL, ETL.
Dimensions and weight:	52.7 × 10.1 × 55.4 cm (screen fix, w × h × d) 7.7 kg (unpacked)
Order numbers:	15.3600 Hedge Hog 4 Console 15.4460 Hedge Hog 4 Console Case 15.4220 Hog 4 Super Widget 15.4230 Hog 4 Single Widget 15.4240 Hog 4 SMPTE/LTC Widget

The delivery is carried out without road case, operational, incl. 1 × LED desklight, dustcover, USB stick, power cable.
12 months world wide warranty.

All rights reserved. Errors, literal mistakes and technical changes reserved.
Named brands are the property of their respective company.

© 2013 Arcus Licht- und Präsentationstechnik GmbH



Arcus Licht- und Präsentationstechnik GmbH
Obermeiers Feld 2 - 4, D-33104 Paderborn, Germany
Phone: +49 (0) 5254 93069 0 · Fax: +49 (0) 5254 93069 29

Mail: info@arcus-lighting.com
Web: <http://www.arcus-lighting.com>
Web: <http://www.hog4.de>